

# P6000 400V 50HZ #IPP

# THE SILENT POWER



Low noise level, it is the ideal generator for use in residential areas or outside normal working hours. It's equipped with a reliable Diesel engine, first class components and complete instrumentation.

Main Features		
Frequency	Hz	50
Voltage	V	400
Power factor	cos φ	0.8
Phase		3

Ratings definition (According to standard ISO8528 1:2005)

Engine specifications		
Engine Brand		Yanmar
Model	L100V Electric	
[50Hz] Exhaust emission level	Stage V	
Engine cooling system		Air
Displacement	cm³	435
Aspiration		Natural
Operating Speed-Nominal	rpm	3000
Speed governor		Mechanical
Fuel		Diesel
Oil capacity		1.6
Starting system		Electric



# **GENSET CONTROL PANELS (IPP)**

Mounted on the genset and complete of: instrumentation, control, protection of the generating set and sockets.



#### COMMANDS

- Start selector switch with key: OFF - ON - START

## **INSTRUMENTATION (DGT)**

- Voltmeter
- Hours-counter
- Frequency meter

# PROTECTIONS

- Circuit breakerIsometer protection (IPP)
- Oil Guard

### TRANSPORTATION KIT

with folding handles



The information is aligned with the Data file at the time of download. Printed on 17/03/2022 (ID 16071)

 $\textcircled{\sc c}2022 \mid \mathsf{PR}\ \mathsf{INDUSTRIAL}\ \mathsf{s.r.l.} \mid \mathsf{All}\ \mathsf{rights}\ \mathsf{reserved} \mid \mathsf{Image}\ \mathsf{shown}\ \mathsf{may}\ \mathsf{not}\ \mathsf{reflect}\ \mathsf{actual}\ \mathsf{package}.$  Specifications subject to change without notice

